
Electricity Retail Data Service (ERDS) Service Definition

Contents

1	Description of service	54
2	Definition of ERDS Users.....	54
3	Service Functionality.....	65
4	System Access and User Management	8
5	Service Availability	9
6	User Support	9
7	Service Levels	10
8	Maximum Demand Volumes.....	1142
9	Reporting.....	1243
10	System Audit	13
11	Data Handling.....	13
12	Security	13

Technical Specification Document

Electricity Retail Data Service (ERDS) Service Definition

Version: 1.1

Effective Date: 4 November 2022

Change History

Version Number	Implementation Date	Reason for Change
0.1	TBD	Initial Draft for November 2019 Technical Specification Approach Consultation
0.2	TBD	Draft for Spring 2021 Switching Consultation
1.0	18 July 2022	Switching SCR Modification R0041
1.1	4 November 2022	R0036
MHHS v0.1	N/A	MHHS required changes: Draft for industry review
MHHS v0.2	N/A	MHHS required changes: Draft updated post industry consultation (change to info in comments only)
MHHS v0.3	N/A	Version Uplifted following CCAG Approval
MHHS v0.4	N/A	Mop up version – updated to include transition text, R0064 and SLAs
MHHS v0.5	N/A	MHHS required changes: Updated to reflect Mop Up consultation comments. To be issued to CDWG for assurance check.
MHHS v0.6	N/A	Issued for M6 Consistency Check consultation. No change from MHHS v0.5
MHHS v1.0	N/A	M6 version approved by CCAG. Updated version number for SCR consultation with no further changes made from previous version.

MHHS v1.1	N/A	Update to reflect MHHS Programme Change Request CR-056 for single appointment message per Metering Point per day – I0241
---------------------------	---------------------	--

1 Description of service

- 1.1. The [Electricity Retail Data Service \(ERDS\)](#) is a [Switching Data Service](#) provided by the [Electricity Retail Data Agent](#). The [ERDS](#)'s purpose is to enable the exchange of [Registration](#) and [Registrable Measurement Point \(RMP\)](#) data between the [Supplier Meter Registration Agents \(SMRAs\)](#), the [Smart Meter Data Service Provider \(SMDSP\)](#), the [Green Deal Central Charging Database \(GDCC\)](#), Electricity Suppliers, Distribution Network Operators (DNOs), Meter Operator Agents (MOAs), the Electricity Enquiry Service (EES), the Market Domain Data Agent (MDDA) and the [Central Switching Service Provider \(CSS Provider\)](#). Paragraph 3 details all of [Market Participant](#)s and the exchanges of data between each entity in greater detail.
- 1.2. The [ERDA](#) is not a [Party](#) to the [Code](#). Where the [ERDA](#) is referenced within this [Code](#), [DNOs](#) are obliged to ensure that the services are provided in line with this [Code](#).
- 1.3. The [ERDA](#) is referenced within a number of [REC Schedules](#), specifically the [Registration Services Schedule](#), [Switching Data Management Schedule](#), [RMP Lifecycle Schedule](#), [Related Metering Points Schedule](#) and [Address Management Schedule](#). This document should be read in conjunction with those [REC Schedules](#).
- 1.4. The [ERDA](#) is one of a number of [Switching Data Service Providers](#) and is therefore captured within the scope of the overall [Switching Service Management](#) arrangements, as defined in the [Switching Service Management Schedule](#). The scope of the [Switching Service Management](#) arrangements is limited to the primary interface between the [ERDA](#) (or its contracted [CSS Interface Provider](#)) and the [CSS Provider](#).
- 1.5. The [ERDA](#) may use a [CSS Interface Provider](#) to exchange [Market Messages](#) with the [Central Switching Service](#). Where this is the case, the [ERDA](#) retains responsibility for its obligations set out within the [Code](#), including this [Service Definition](#).

2 Definition of [ERDS Users](#)

- 2.1. The [ERDS](#) interfaces with the following users:

- (a) [CSS Provider](#);
- (b) [SMRAs](#);
- (c) [SMDSP](#);
- (d) [GDCC Provider](#);

- (e) DNOs;
- (f) EES;
- (g) MDDA; and
- (h) Electricity Suppliers.

2.2. Further details regarding the interaction with each of these users is included in Paragraph 3.

3 Service Functionality

3.1. The key function of the [ERDS](#) is to pass [Market Messages](#) between [SMRAs](#), the [SMDSP](#), the [GDCC](#), Electricity Suppliers, DNOs, MOAs, the EES, the MDDA and the [CSS Provider](#) in accordance with the [Registration Services Schedule](#), [Switching Data Management Schedule](#), [RMP Lifecycle Schedule](#), [Related Metering Points Schedule](#) and [Address Management Schedule](#). These [Market Messages](#) must conform to the message structure defined in the [Data Specification](#) which may require the [ERDS](#) to carry out transformation activities. The transformation rules are also defined within the [Data Specification](#).

[Market Messages](#) sent by the [ERDA](#)

3.2. The [ERDA](#) shall send [Market Messages](#) to the [CSS Provider](#) in a consistent format as described in the [Data Specification and](#) within the timescales referenced in Paragraph 7. The data sent from the [ERDA](#) to the [CSS Provider](#) is summarised below:

- (a) **[Regulatory Alliance](#) data** - identifies whether the necessary regulatory arrangements exist between an [Electricity Supplier](#) and a [DNO](#). Where the [ERDA](#) becomes aware of a new or updated [Regulatory Alliance](#), the [ERDA](#) shall send the [CSS Provider](#) the relevant message providing the updated [Regulatory Alliance](#). This is specified in the [Switching Data Management Schedule](#).
- (b) **[Metering Point](#) data** - Where the [ERDA](#) becomes aware of an amendment to [Metering Point](#) data, as described within the [RMP Lifecycle Schedule](#) or [Related Metering Points Schedule](#), including:
 - (i) a change in circumstances in respect of a [Metering Point](#) such that the [RMP Status](#) needs to be updated, and sent to the [CSS Provider](#) via the relevant [Market Message](#) in respect of that [RMP](#);

- (ii) a change to the energy flow direction of a [Metering Point](#); or
 - (iii) the creation or update of a [Related Metering Point Relationship](#).
- (c) **Meter Point Location Address** – Where the [DNO](#) creates or makes an amendment to the [Meter Point Location \(MPL\) Address](#), the [ERDA](#) shall send the [CSS Provider](#) the relevant [Market Message](#) providing the updated [MPL Address](#). This is specified in the [Address Management Schedule](#).
- (d) **Supplier Agent and SMDR Appointment and Meter Asset Provider update** – The [ERDA](#) will, in accordance with the [RMP Lifecycle Schedule](#), notify the [CSS Provider](#) using the relevant [Market Message](#) where it becomes aware of:
- (i) changes to the [Meter Asset Provider](#)(s) recorded at a [Metering Point](#) within [SMRS](#);
 - (ii) an appointment of, or change to the MOA or SMDR recorded for a MHHS [Metering Point](#) within [SMRS](#); or
 - (iii) an appointment of, or change to one or more [Supplier Agents](#) recorded for a Non-MHHS [Metering Point](#) within [SMRS](#). [SMRS](#) and the [ERDS](#) are logical interfaces within the [DNO](#)'s estate, therefore, interactions between the two services are not defined as [Market Messages](#).
- (e) **Green Deal Plans** – where the [ERDA](#) receives a notification from the GDCC of the creation or update of a Green Deal Plan associated to a Metering Point, the [ERDA](#) shall send the [CSS Provider](#) the relevant message. This is specified in the [RMP Lifecycle Schedule](#).
- (f) **DCC Service Flag** – where the [ERDA](#) receives a notification from the SMDSP updating the DCC Service Flag for a Metering Point, the [ERDA](#) shall send the [CSS Provider](#) the relevant message. This is specified in the [RMP Lifecycle Schedule](#).
- 3.3. The [ERDA](#) sends Metered Data and RMP Status data relating to Non-MHHS Metering Points in a single Market Message combined with data held by the [SMRS](#) to the [EES](#) following [ERDS](#) Total Daily Processing.

[Market Messages received by the ERDA](#)

- 3.4. The [CSS Provider](#) sends [Registration](#) and [Retail Energy Location Address](#) data to the [ERDA](#) in 'real time'. Response times by the [ERDA](#) are specified in Paragraph 7.
- 3.5. Where the [ERDA](#) receives data, in accordance with the [Registration Services](#)

[Schedule](#), a new [Registration](#) or an update to an existing [Registration](#), that data must be made available to the [SMRA](#) within the timescales referenced in Paragraph 7.

- 3.6. The [MDDA](#) sends [Market Messages](#) to the [ERDA](#) in a consistent format as described in the [Data Specification](#). The data sent from the [MDDA](#) to the [ERDS](#) includes [Market Participant Data](#) utilised by the [ERDA](#) in order to manage [Regulatory Alliances](#).
- 3.7. Meter Operator Agents send [Market Messages](#) to the [ERDA](#) as required within the [Metering Operations Schedule](#), in a consistent format as described in the [Data Specification](#).
- 3.8. [Electricity Suppliers](#) send [Market Messages](#) to the [ERDA](#) as required within the [Related Metering Points Schedule](#), in a consistent format as described in the [Data Specification](#).

[Smart Meter Data Service Provider](#) to ERDA Messages

- 3.9. The [Smart Meter Data Service Provider \(SMDSP\)](#) sends [Market Messages](#) to the [ERDA](#) as required within the [Smart Energy Code](#), in a consistent format as described in the [Data Specification](#).

[GDCC](#) to [ERDA](#) Messages

- 3.10. The GDCC Provider sends [Market Messages](#) to the [ERDA](#) as required in the [Green Deal Arrangements Schedule](#), in a consistent format as described in the [Data Specification](#).

4 System Access and User Management

- 4.1. The [ERDS](#) does not require any individual user management functionality beyond the user management functionality that each [DNO](#) requires for the operation of the service, which is not defined within this document. No provisioning of access to users outside of the [DNO](#) is required.
- 4.2. The [ERDA](#) is classed as a [CSS User](#) and must therefore comply with the requirements within the [CSS Schedule](#). No specific access is granted to the [CSS Provider](#) by the [ERDA](#).

- 4.3. Interfaces to the [GDCC Provider, Electricity Suppliers and the MDDA](#) utilise the [Data Transfer Network](#) for the transportation of [Market Messages](#) to and from a [Data Transfer Network](#) gateway within each [DNO](#)'s estate. As such, a [DNO](#) is responsible for the transfer of [Market Messages](#) between its [Data Transfer Network](#) gateway and the [ERDA](#). For the purposes of the [Data Transfer Network](#), the [ERDA](#) and the [SMRA](#) are identified as the same Market Role Code within Industry Standing Data.

5 Service Availability

- 5.1. The [ERDS](#) shall be provided 24 hours, seven days a week for the receipt and acknowledgment of [Market Messages](#) from the [CSS Provider](#), except during [Scheduled Maintenance](#) periods and unplanned outages.
- 5.2. Service availability for the receipt and acknowledgement of [Market Messages](#) from the [CSS Provider](#) shall be 99.75% for each calendar month (excluding [Scheduled Maintenance](#)).
- 5.3. [Scheduled Maintenance](#) shall not occur between 16:00 and 01:00 hours. In the event of [Scheduled Maintenance](#) that impacts the service that the [ERDA](#) is providing under the [REC](#), the [ERDA](#) shall provide notice to the [Switching Operator](#) for inclusion in the forward schedule of change, in accordance with the [Switching Service Management Schedule](#).
- 5.4. In the event of an unplanned outage:
- (a) the [ERDA](#) shall notify the [Switching Operator](#) in accordance with the [Switching Service Management Schedule](#); and
 - (b) the [System](#) shall resume operation within one hour.

6 User Support

- 6.1. The [ERDS](#) does not have an externally facing service desk. Any [Switching Incidents](#) and [Switching Service Requests](#) shall be raised via the [Switching Portal](#). The [ERDA](#) shall provide second line support in accordance with this Paragraph 6 and the [Switching Service Management Schedule](#).
- 6.2. The [ERDA](#) shall support the response and resolution times for the following [Switching Incident](#) categories.

- (a) Priority 1 – for [Switching Incidents](#) causing critical impact and significant financial loss / disruption - 30 minute response with a four hour resolution time;
- (b) Priority 2 – for [Switching Incidents](#) causing non-critical impact with non-significant financial loss / disruption - one hour response with a 24 hour resolution time;
- (c) Priority 3 – for [Switching Incidents](#) causing adverse impact but can be reduced to moderate adverse impact - three [Working Hour](#) response with a three [Working Day](#) resolution time;
- (d) Priority 4 – for [Switching Incidents](#) causing minimal impact - one [Working Day](#) response with a 10 [Working Day](#) resolution time.

7 [Service Levels](#)

Response to [CSS Market Messages](#)

- 7.1. Each [ERDS](#) shall respond to [Market Messages](#) relating to secured Switches from the CSS Provider at Gate Closure (from the [CSS Provider](#) relating to secured [Switches](#) at [Gate Closure](#) (from the point at which the [System](#) receives the first message to the point at which it sends the acknowledgement of receipt for the last message) as follows:

Performance Parameter	Performance Level
Processing of data received from the CSS relating to Secured Active Switches during Gate Closure period	
Up to and including average daily volume	mean response time of 20 minutes or less
Up to and including average daily volume	90th percentile response time of 25 minutes or less
Above average daily volume and up to and including until peak daily volume	mean response time of 35 minutes
Above average daily volume and up to and including until peak daily volume	90th percentile response time of 40 minutes

- 7.2. Each [ERDS](#) shall respond to [Market Messages](#) from the [CSS Provider](#), other than within the [Gate Closure](#) period, as follows:

Performance Parameter	Performance Level
Processing of data received from the CSS outside of the Gate Closure period	
Up to and including average hourly volume	mean response time of six seconds

	or less
Up to and including average hourly volume	90th percentile response time of 10 seconds or less
Above average hourly volume and up to and including until peak hourly volume	mean response time of 10 seconds or less
Above average hourly volume and up to and including until peak hourly volume	90th percentile response time of 15 seconds or less

Processing CSS Market Messages Received by the [ERDA](#)

7.3. Data received by the [ERDA](#) from the CSS Provider shall be processed within timescales that allow the associated SMRA to meet its obligations under the BSC.

Provision of CSS Market Messages by the ERDA

7.3A Subject to Paragraph 7.3B, the ERDA shall provide any data defined in Paragraph 3.2 to the CSS Provider by 06:00hrs the following Working Day where the data is received prior to 23:00hrs and by 06:00hrs on the second Working Day where the data is received after 23:00hrs.

7.3B The ERDA shall provide Supplier Agent and SMDR Appointment data in a single CSS00200 Market Message per Metering Point by 23:00 hours on the day the Appointment confirmation is issued by the equivalent SMRA.

Commented [HT1]: I0241 update (M8-030) - addition of requirement for Supplier Agent and SMDR appointments to be provided in a single appointment message

Management of BCDR events

7.4. Where a BCDR event is invoked, the Recovery Time Objective for the [ERDS](#) will be:

- (a) four hours target time; and
- (b) eight hours maximum time.

8 Maximum Demand Volumes

8.1. Individual maximum demand volumes shall be determined by the [Code Manager](#) for each [ERDA](#) on an annual basis using the data provided by the [CSS Provider](#) in accordance with Clause 9.24 of the main body of this [Code](#), for the month of October each year. Each [ERDA](#)'s market share shall be calculated by the [Code Manager](#) based on the total number of [Metering Points](#) connected to the relevant [DNO](#)'s network, divided by the total number of [Metering Points](#) Registered within the [CSS](#). This market share value shall be applied to each of the overall electricity

maximum demand volumes in Paragraph 8.3, with the addition of a 10% headroom to allow for growth in the number of connected [Metering Points](#).

- 8.2. Where maximum demand volumes are breached within a given month, the [ERDA](#) shall report the breach incident, and any impacts against the service, to the [Code Manager](#). The [Code Manager](#) may initiate a [Change Proposal](#) to increase the overall maximum demand volumes in Paragraph 8.3 or take remedial steps to prevent recurrence of the breach.

Processing of data from the [CSS Provider](#)

- 8.3. The maximum demand volumes to be used in the calculation described in Paragraph 8.1 are:

- (a) processing an average daily volume of 24,534 successful Switch Requests;
- (b) processing a peak daily volume of 163,328 successful Switch Requests;
- (c) processing an average hourly volume of 2,030 successful Switch Requests;
- (d) processing a peak hourly volume of 14,674 successful Switch Requests;
- (e) processing an annual volume of 8,961,000 successful Switch Requests;
- (f) processing an annual volume of 217,964 Initial Registration Requests;
- (g) in exceptional circumstances, processing 145,000 [Switch Requests](#), in addition to the average daily volume;
- (h) storing 32,074,000 [Metering Points](#); and
- (i) supporting a 217,964 increase in the number of [Metering Points](#) in the first year of the [CSS](#)'s operation.

Processing of data from the [SMRS](#)

- 8.4. The [ERDS](#) receives data from the [SMRS](#). Since this is a logical interface and there is no specific storage within the [ERDS](#), no constraints are identified with receipt of this data from this source.

9 Reporting

- 9.1. The [ERDS](#) shall provide a monthly performance report to the [Code Manager](#) for

consideration by the [Performance Assurance Board](#), providing details of overall service performance against requirements set out within this [Service Definition](#).

10 System Audit

- 10.1. Each [ERDS](#) need not retain specific [Market Messages](#), however they shall maintain an audit trail of messages received and responses sent (inbound and / or outbound messages).

11 Data Handling

- 11.1. The [ERDA](#) shall receive data from the [CSS Provider](#) and provide an initial response within the timescales set out in Paragraph 7.
- 11.2. When incoming updates to the [ERDA](#) are processed on a periodic basis, [Market Messages](#) from the [CSS Provider](#) shall be processed before updates originating from [Electricity Suppliers](#).
- 11.3. Other than for audit purposes, no retention of data is required by this service in normal operation.
- 11.4. The [ERDS](#) shall be able to detect loss of [Market Messages](#) sent from it and duplication of [Market Messages](#) transferred to it.
- 11.5. Upon receipt of a [Market Message](#) that indicates / infers a data inconsistency with the [CSS](#), the [ERDA](#) will initiate the required steps to determine the necessary resolution.

12 Security

- 12.1. Security arrangements associated with the data exchange between each [ERDS](#) and other [Market Participants](#) and [Switching Data Service Providers](#) are covered by the following arrangements:
- (a) [CSS Provider](#) – the [ERDS](#) is classified as a [CSS User](#) and the [CSS](#) security requirements apply, as set out in the [CSS Schedule](#).
- (b) [Supplier Meter Registration Agents](#) – the [SMRS](#) is a service delivered by individual [DNOs](#), therefore there is no physical interface required between the [ERDA](#) and

the [SMRAs](#).

- (c) [Smart Meter Data Service Provider](#) – the interface with the [SMDSP](#) is defined within the [Smart Energy Code](#); therefore, the security requirements in relation to this interface reflect [SEC](#) requirements.
- (d) [GDCC Provider](#) - the interface with the [GDCC Provider](#) utilises the [Data Transfer Network](#), with security information reflected in the [Data Transfer Services Agreement](#).
- (e) DNOs - the ERDS is a service delivered by individual DNOs, therefore there is no physical interface.
- (f) Market Domain Data Agent - the ERDS receives electricity Market Participant Data from the MDDA via a data flow transferred via the Data Transfer Network which requires the ERDS to have a Data Transfer Network connection. The associated security requirements form part of the Data Transfer Services Agreement.
- (g) Electricity Suppliers - the interface with Electricity Suppliers utilises the Data Transfer Network, with security information reflected in the Data Transfer Services Agreement.

12.2. In the event that an [ERDA](#) detects a potential or suspected security breach impacting [Switching](#) related [Systems](#), it shall raise a [Switching Incident](#) (in accordance with the [Switching Service Management Schedule](#)) immediately.