SCHE	SCHEDULE 28								
Related Meteri	ng Points Schedule								
Version: 1.0	Effective Date: 18 July 2022								
Domestic Suppliers	Mandatory for Electricity Suppliers								
	N/A for Gas Suppliers								
Non-Domestic Suppliers	Mandatory for Electricity Suppliers								
	N/A for Gas Suppliers								
Gas Transporters	N/A								
Distribution Network Operators	Mandatory								
DCC	N/A								
Metering Equipment Managers	N/A								
Non Party REC Service Users	N/A								

Related Metering Points Schedule

1 Code Company

Change History

Version Number	Implementation Date	Reason for Change
0.1	N/A	Draft agreed for June 2019 consultation
0.2	N/A	Updated draft for Summer 2020 publication
0.3	N/A	Updated draft for November 2020 baselining
0.4	N/A	Updated draft for Spring 2021 Switching Consultation
1.0	18 July 2022	Switching SCR Modification R0041
<u>MHHS v0.1</u>	<u>N/A</u>	MHHS required changes: Draft for industry review
MHHS v0.2	<u>N/A</u>	MHHS required changes: updated draft post_industry consultation
<u>MHHS v0.3</u>	<u>N/A</u>	Version Uplifted following CCAG Approval
<u>MHHS v0.4</u>	<u>N/A</u>	<u>Mop up version – updated to</u> include transition text, REC CP R0064, Programme CR025 and DIN560 / DIN354
<u>MHHS v0.5</u>	<u>N/A</u>	<u>MHHS required changes: Updated</u> <u>to reflect Mop Up assurance</u> <u>comments. To be issued to CDWG</u> <u>for recommendation to CCAG.</u>
<u>MHHS v0.6</u>	<u>N/A</u>	Issued for M6 Consistency Check consultation. No change from <u>MHHS v0.5</u>

Related Metering Points Schedule

2 Code Company Copyright 20232 Retail Energy

Contents Table

Par	agraph	Heading	Page
1	Introducti	on	4
2	Creation o	of a Related Metering Point Relationship	5
3	Amendme	ent to an existing Related Metering Point Relationship	<u>1097</u>
4	Ending of	Related Metering Point Relationship	14 <u>13</u> 8
5	Distributio	on Network Operator Management of Related Metering Points	17 <u>16</u> 9
6	Data Qual	ity Requirements <u>1</u>	7 <u>16</u> 10

3 Code Company

1 Introduction

1.1 This REC Schedule documents the procedures for Electricity Suppliers to create, maintain and end the relationship between two or more Related Metering Points. For MHHS Metering Points, Related Metering Point relationships are maintained by Electricity Suppliers and notified to the Supplier Metering Registration Service using DIP Market Messages, Related Metering Points are mastered in the Electricity Retail Data Service and provided by that service to the Central Switching Service.

1.2 An Electricity Supplier can create a Related Metering Point relationship between two or more Import Metering Points (other than Export Metering Points) for which it is the Registered Supplier where:

- (a) for Non Half HourlyWhole Current Metering Points:
 - all the Metering Points supply electricity to the same Consumer at the same Location (or at any part of the same Location);
 - (ii) the Meter Point Location Address and the Retail Energy Location Address are the same for each Metering Point; and
 - (iii) the Electricity Supplier has identified that an appropriate Distribution Use of System Charge tariff, as set out within the DCUSA, is currently applicable to the Primary Related Metering Point and Secondary Related Metering Point(s), or can become applicable to those Metering Points following creation of the Related Metering Point relationship; and

(iii)(iv) the Connection Type is Whole Current; or

- (b) for Half HourlyCurrent Transformer Metering Points:
 - the Metering Points supply electricity to the same Consumer at the same Location (or at any part of the same Location);
 - (ii) the Meter Point Location Address and the Retail Energy Location Address are the same for each Metering Point;
 - (iii) the Distribution Network Operator (DNO) has notified the Registered Supplier that some or all of the Distribution Use of System Charges are aggregated and charged against a single Metering Point; and
 - (iv) that aggregated Distribution Use of System Charges are only levied against the Primary Related Metering Point; and
 - (iv) the Connection Type includes the use of Measurement Transformers.or
 - for Non Half Hourly Unmetered Supplies, each Metering Point relates to an Unmetered Supply which is recorded within a single Unmetered Supply Certificate.
- <u>1.41.3</u> Each Related Metering Point relationship must be composed of one Primary Related Metering Point and one or more Secondary Related Metering Points.

<u>1.51.4</u> A Related Metering Point can only be part of a single Related Metering Point relationship.

Δ

Code Company

Copyright 20232 Retail Energy

Commented [SJ1]: Mop Up Update - Updated to clarify that this text only applies to MHHS Metering Points for transition text

Commented [SJ2]: Mop Up Update - amended DIP Interface to DIP Market Message to align to Schedule 1

Commented [SJ3]: Removed as this will be managed through DIP messages with the SMRS

Commented [SJ4]: Amended for clarity, to avoid confusion with the import / export linkage created for MHHS

Commented [SJ5]: P434 is removing NHH unmetered so they will all use a single inventory and no need to relate

- 1.61.5 Where the Registered Supplier for the Primary Related Metering Point has more than one Market Participant Role, the Registered Supplier must use the Market Participant Role by which it is identified in respect of the Primary Related Metering Point when seeking to add one or more Secondary Related Metering Point(s).
- <u>1.71.6</u> All subsequent Registrations for each Related Metering Point will have the same Supply Effective From Date and Supply Effective Through Date.
- 1.81.7 A Switch Request can only be submitted to the Central Switching Service for a Related Metering Point identified as the Primary Related Metering Point (as further described in the Registration Services Schedule).
- 1.8
 The Related Metering Point management process relies on messages sent between the Registered Supplier and the relevant Electricity Retail Data AgentSupplier Meter Registration

 Agent for MHHS Metering Points and Electricity Retail Data Agent for Non MHHS Metering Points, as described in Paragraphs 2, 3 and 4 of this REC Schedule.
- 1.9 The sending of DIP Market Messages detailed in this REC Schedule is mandatory. Where DIP Market Messages are used to send information to a Distribution Network Operator from the relevant Supplier Meter Registration Agent, the Distribution Network Operator shall subscribe to receive the relevant DIP Market Message or, access the information via internal communication channels.

2 Creation of a Related Metering Point Relationship

- 2.1 This procedure is to be used when the Registered Supplier identifies, or is notified by another Market Participant, that a circumstance described in paragraph 1.2 exists.
- 2.2 Where a Registered Supplier wants to create a new Related Metering Point relationship, it shall notify the <u>Electricity Retail Data AgentSupplier Meter Registration Agent</u> for MHHS Metering Points and Electricity Retail Data Agent for Non-MHHS Metering Points, identifying which Metering Point is to be the Primary Related Metering Point and which the Secondary Related Metering Point(s).
- 2.3 The prerequisites for this procedure are that:
 - the Metering Points which are to become Related Metering Points each have the same RMP Status of Operational<u>or Created;</u>
 - (b) there is no Pending Registration for the Metering Points;
 - the same Electricity Supplier (using the same Market Participant Role) holds an Active Registration for each Metering Point;
 - (d) each Metering Point has the same classification as either a Domestic Premises or a Non-Domestic Premises;
 - (e) the Registered Supplier has appointed the same <u>Meter Operator Agent (MOA)</u> <u>HEM</u> for each Metering <u>Point</u>, or (in the case of <u>Unmetered Supplies</u>) the same <u>UMSO is</u> responsible for each <u>Metering Point</u>; and
 - (f) the Metering Points are not members of a different existing Related Metering Point relationship; and.

Related Metering Points Schedule

Code Company

5

Copyright 202<u>3</u>2 Retail Energy

Commented [SJG]: Mop Up Update - additional text to differentiate MHHS and Non MHHS requirements for transition Commented [AW7]: Amended throughout to reflect BP010B,

which introduces a new IF-019 to replace the D0386

Commented [SJ8]: Post Mop Up Assurance Review -Removal of requirements on DNOs to receive messages via the DIP (links to CR029)

Commented [SJ9]: Mop Up Update - additional text to differentiate MHHS and Non MHHS requirements for transition

Commented [SJ10]: Post consultation update - added Created following confirmation that new relationships can be established for Metering Points with a status of Created as part of DIN105

Commented [SJ11]: Post consultation update - Programme position confirmed via DIN105 that this will not be included in validation rules - no change to drafting, regulatory requirement to be maintained

Commented [SJ12]: Mop Up Change - amended terminology from MEM to MOA to reflect approved CP R0064

Commented [SJ13]: Post consultation update - programme position confirmed via DIN 105 that validation of this rule is captured in BP011C - no change to drafting.

(g) for Unmetered Supplies, the Electricity Supplier has received an Unmetered Supply Certificate from the UMSO which contains a set of Metering Points to be related, as per the process set out in the BSC.

Related Metering Points Schedule

ර Code Company 2.4 The detailed process and timings for creating a Related Metering Point relationship where all Metering Points are MHHS Metering Points the procedure are further described in the following interface table:

c	are further described in the	e following interface table:					
Ref	When	Action	From	То	Interface	Means	Commented [SJ15]: Existing drafting amended to reflect BP010B and BP011C
<u>.4.1</u>	Where the Electricity Supplier identifies that	Assign a Related Metering Point Meter Timeswitch Code (550 – 799)	Electricity Supplier	SMRS	In accordance with the BSC	N/A	
	two or more Metering Points meet the criteria in Paragraph 1.2.	to each of the Related Metering Points and update <mark>SMRS</mark>.					Commented [SJ16]: Merged first two steps to reflect removal of MTC
2.4. <u>1</u> 2	Following 2.4.1. Where the Electricity Supplier identifies that two or more Metering Points meet the criteria in Paragraph 1.2.	Create a Related Metering Point relationship for the Primary Related Metering Point and Secondary Related Metering Point(s).	Registered Supplier	Electricity Retail Data Agent Supplier Meter Registration Agent	D0386 Manage Metering Point Relationships <u>MHHS IF-</u> 019 Maintain MPAN Relationships	DTNDIP Interface	Commented [SJ17]: Mop Up Update - added interface names throughout
2.4. <u>2</u> 3	Following 2.4. <u>1 and</u> within the timescales set out in the BSCP7062	Validate request to create a Related Metering Point relationship as set out in Paragraph 1 .	Electricity Retail Data Agent Supplier Meter Registration Agent		Internal Process		Commented [SJ18]: Post consultation update - added reference to BSCPs as agreed at the July CDWG
2.4. <u>3</u> 4	Following 2.4. <u>2</u> 3 if request is not valid.	Provide notification that the request has failed validation and the reasons for failure.	Electricity Retail Data Agent Supplier Meter Registration Agent	Registered Supplier	D0386 Manage Metering Point MHHS IF-D20RelationshipsTBC Maintain MPAN Relationships Outcome	DTNDIP Interface	Commented [SJ19]: Post consultation update to reflect Programme confirmation that rejection is via the IF020 through DIN 105 Formatted: Highlight
2.4. <u>45</u>	Following 2.4. <u>2</u> 4 if request is valid.	Provide notification that the request has been validated.Publish Related Metering Point relationship data	Electricity Retail Data Agent Supplier Meter	Registered Supplier	D0386 Manage Metering Point Relationships <u>MHHS IF-</u>	DTNDIP Interface	

Commented [SJ14]: Mop Up Update - additional text to differentiate MHHS and Non MHHS requirements for transition

Related Metering Points Schedule

7

		Registration Agent	DNO MEM MOA Data Service BSC Central Systems Electricity Enquiry Service Provider	020_Maintain MPAN Relationships Outcome		Commented [SJ20]: Mop Up Change - amended terminology from MEM to MOA to reflect approved CP R0064
 Following 2.4.4, in accordance with BSCP706.	Assess whether the same MOA Advanced Data Service Agent and / or Smart Data Service Agent is Appointed to the Primary Metering Point and Secondary Metering Points. Where the same MOA, Advanced Data Service Agent and / or Smart Data Service Agent is not Appointed to the Primary Metering Point and Secondary Metering Points, initiate auto de-appointment and auto Appointment in accordance with BSCP706 and the Metering Operations Schedule.	Supplier Meter Registration Agent		Refer to BSCP706 and the Metering Operations Schedule.		 Commented [SJ21]: SMRS review of linkage and auto appointment taken from BP011C Commented [SJ22]: Mop Up Change - amended terminology from MEM to MOA to reflect approved CP R0064 Commented [SJ24]: Mop Up Update - new section added to the MO Schedule to reflect the auto appointment / de-appointment process Includes DIN354 / 560 introduced through IR4. Commented [SJ23]: Mop Up Change - amended terminology from MEM to MOA to reflect approved CP R0064
the ERDA becomes	Update the Primary Related Metering Point and Secondary Related Metering Point(s).	Electricity Retail Data Agent	CSS Provider	RMP Associations	CSS API	

			-		
2.4. <u>7</u> 7	Following 2.4. <u>6</u> 6	Perform asynchronous validation:	CSS Provider	Internal Process	
	where the message				
	passes synchronous	If valid, update RMP Record.			
	validation.	<i>,</i> , ,			
	, and a com	If not valid, the CSS Provider shall			
		resolve the error in accordance			
		with the relevant Error Resolution			
		Paths.			

2.4A The detailed process and timings for creating a Related Metering Point relationship where all Metering Points are Non-MHHS Metering Points are further described in the following interface table:

Ref	When	Action	<u>From</u>	<u>To</u>	Interface	<u>Means</u>
2.4.1A	Where the Electricity	Assign a Related Metering Point	Registered Supplier	<u>SMRS</u>	In accordance with the	<u>N/A</u>
	Supplier identifies that	Meter Timeswitch Code (550 – 799)			BSC	
	two or more Metering	to each of the Related Metering				
	Points meet the	Points and update SMRS.				
	criteria in Paragraph					
	<u>1.2.</u>					
<u>2.4.2A</u>	Following 2.4.1A.	Create a Related Metering Point	Registered Supplier	Electricity Retail	D0386 Manage	DTN
		relationship for the Primary Related		Data Agent	Metering Point	
		Metering Point and Secondary			Relationships	
		Related Metering Point(s).				
2.4.3A	Following 2.4.2A.	Validate request to create a Related	Electricity Retail		Internal Process	
		Metering Point relationship as set	Data Agent			
		out in Paragraph 1.				
2.4.4A	Following 2.4.3A if	Provide notification that the	Electricity Retail	Registered	D0386 Manage	DTN
	request is not valid.	request has failed validation and	Data Agent	Supplier	Metering Point	
		the reasons for failure.			<u>Relationships</u>	

9

Commented [SJ25]: Mop Up Update - additional table to differentiate MHHS and Non MHHS requirements for transition

<u>2.4.5A</u>	Following 2.4.4A if request is valid.	Provide notification that the request has been validated.	Electricity Retail Data Agent	Registered Supplier	D0386 Manage <u>Metering Point</u> <u>Relationships</u>	
<u>2.4.6A</u>	Following 2.4.5A.	Update the Primary Related Metering Point and Secondary Related Metering Point(s).	<u>Electricity Retail</u> Data Agent	<u>CSS Provider</u>	RMP Associations	CSS API
<u>2.4.7A</u>	Following 2.4.6A where the message passes synchronous validation.	Perform asynchronous validation: If valid, update RMP Record. If not valid, the CSS Provider shall resolve the error in accordance with the relevant Error Resolution Paths.	<u>CSS Provider</u>		Internal Process	

3 Amendment to an existing Related Metering Point Relationship

- 3.1 This procedure is to be used when the Registered Supplier wants to make changes to an existing Related Metering Point relationship resulting in Secondary Related Metering Points being removed from or added to an existing relationship, without the relationship being ended.
- 3.2 Where a Registered Supplier needs to change which Related Metering Point is the Primary Related Metering Point, it shall first end the existing relationship (Paragraph 4) and then create a new relationship (Paragraph 2).
- 3.3 The detailed process and timings for amending a Related Metering Point relationship where all Metering Points are MHHS Metering Points the procedure are further described in the following interface table:

Ref	When	Action	From	То	Interface	Means
3.3.1	Following the	Amend the existing Related	Registered	Electricity Retail	D0386 Manage	DTNDIP
	requirements of	Metering Point relationship by	Supplier	Data Agent	Metering Point	Interface
	Paragraph 3.1	removing each Secondary Related		Supplier Meter	RelationshipsMHHS IF-	
	being met.	Metering Point no longer in the				

10

Copyright 202<u>3</u>2 Retail Energy Code Company

Commented [SJ26]: Mop Up Update - additional text to differentiate MHHS and Non MHHS requirements for transition

		existing relationship and/or adding each Secondary Related Metering Point that is being included in the existing relationship.		Registration Agent	<mark>019</mark> Maintain MPAN Relationships			Commented [SJ27]: Mop Up Update - added interface ames throughout
3.3.2	Following 3.3.1 <u>and</u> within the timescales set out in the BSCP706	Validate request to create <u>amend</u> a Related Metering Point relationship as set out in Paragraph 1 .	Electricity Retail Data Agent Supplier Meter Registration Agent		Internal Process			
3.3.3	Following 3.3.2 if request is not valid.	Provide notification that the request has failed validation and the reasons for failure.	Electricity Retail Data Agent Supplier Meter Registration Agent	Registered Supplier	D0386 Manage Metering Point-MHHS IF-020Relationships <u>TBC</u> Maintain MPAN Relationships Outcome	DTNDIP Interface	P tr	commented [SJ28]: Post consultation update to reflect rogramme confirmation that rejection is via the IF020 arough DIN 105 ormatted: Highlight
3.3.4	Following 3.3.2 if request is valid.	Provide notification that the request has been validated. Publish Related Metering Point relationship data	Electricity Retail Data Agent Supplier Meter Registration Agent	Registered Supplier DNO MEMMOA Data Service BSC Central Systems Electricity Enquiry Service Provider	D0386 Manage Metering Point RelationshipsMHHS IFO- 020 Maintain MPAN Relationships Outcome	DTN <u>DIP</u> Interface	C fr	commented [SJ29]: Mop Up Change - amended termin om MEM to MOA to reflect approved CP R0064

3.3.5	Following 3.3.4, in	Assess whether the same MOA,	Supplier Meter		Refer to BSCP706 and	<u>N/A</u>	Commented [SJ30]: Mop Up Update - new section added to
	accordance with	Advanced Data Service Agent and /	Registration		the Metering		the MO Schedule to reflect the auto appointment / de- appointment process Includes DIN354 / 560 introduced
	BSCP706.	or Smart Data Service Agent is	Agent		Operations Schedule.		through IR4.
		Appointed to the Primary Metering					Commented [SJ31]: Mop Up Change - amended terminology
		Point and Secondary Metering					from MEM to MOA to reflect approved CP R0064
		Points.					
		Where the same MOA, Advanced					Commented [SJ32]: Mop Up Change - amended terminology
		Data Service Agent and / or Smart					from MEM to MOA to reflect approved CP R0064
		Data Service Agent is not Appointed					
		to the Primary Metering Point and					
		Secondary Metering Points, initiate					
		auto de-appointment and auto					
		Appointment in accordance with					
		BSCP706 and the Metering					
		Operations Schedule.					
3.3. <u>6</u> 5	Following 3.3.4, where	Add or remove the-Secondary	Electricity Retail	CSS Provider	RMP Associations	CSS API	
	the ERDA becomes	Related Metering Point(s)	Data Agent				
	aware of a valid						
	change to a Related						
	Metering Point						
	<u>relationship</u> .						
3.3. <u>7</u> 6	Following 3.3. <u>56</u>	Perform asynchronous validation:	CSS Provider		Internal Process		
	where the message						
	passes synchronous	If valid, update RMP Record.					
	validation.						
		If not valid, the CSS Provider shall					
		resolve the error in accordance					
		with the relevant Error Resolution					
		Paths.					

3.3A The detailed process and timings for amending a Related Metering Point relationship where all Metering Points are Non-MHHS Metering Points are further described in the following interface table:

12

Commented [SJ33]: Mop Up Update - additional table to differentiate MHHS and Non MHHS requirements for transition

Ref	When	Action	<u>From</u>	<u>To</u>	Interface	Means
<u>3.3.1A</u>	Following the	Amend the existing Related	Registered	Electricity Retail	D0386 Manage	DTN
	requirements of	Metering Point relationship by	<u>Supplier</u>	Data Agent	Metering Point	
	Paragraph 3.1	removing each Secondary Related			<u>Relationships</u>	
	being met.	Metering Point no longer in the				
		existing relationship and/or adding				
		each Secondary Related Metering				
		Point that is being included in the				
		existing relationship.				
<u>3.3.2A</u>	Following 3.3.1A.	Validate request to create a Related	Electricity Retail		Internal Process	
		Metering Point relationship as set	Data Agent			
		out in Paragraph 1.				
<u>3.3.3A</u>	Following 3.3.2A if	Provide notification that the	Electricity Retail	Registered	D0386 Manage	DTN
	request is not valid.	request has failed validation and	Data Agent	<u>Supplier</u>	Metering Point	
		the reasons for failure.			<u>Relationships</u>	
3.3.4A	Following 3.3.2A if	Provide notification that the	Electricity Retail	Registered	D0386 Manage	DTN
	request is valid.	request has been validated.	Data Agent	Supplier	Metering Point	
					<u>Relationships</u>	
3.3.5A	Following 3.3.4A.	Add or remove the Secondary	Electricity Retail	CSS Provider	RMP Associations	CSS API
		Related Metering Point(s)	<u>Data Agent</u>			
3.3.6A	Following 3.3.5A	Perform asynchronous validation:	CSS Provider		Internal Process	
	where the message					
	passes synchronous	If valid, update RMP Record.				
	validation.					
		If not valid, the CSS Provider shall				
		resolve the error in accordance				
		with the relevant Error Resolution				
		Paths.				

4 Ending of Related Metering Point Relationship

- 4.1 This procedure is used when the Registered Supplier identifies that a circumstance described in paragraph 1.2 no longer exists, and that the Primary Metering Point will be Terminated or remain Operational but no longer a Related Metering Point.
- 4.2 Ending a Related Metering Point relationship is a prerequisite for the Electricity Retail Data Agent to change the RMP Status of a Related Metering Point to Terminated.
- 4.3 The detailed process and timings for <u>ending a Related Metering Point relationship where all Metering Points are MHHS Metering Points</u> the procedure are further described in the following interface table:

Ref	When	Action	From	То	Information Required	Method	
4.3.1	Where the Electricity Supplier identifies that	Update that the Related Metering Point relationship has ended.	Registered Supplier	Electricity Retail Data Agent	D0386 Manage Metering Point	DTNDIP Interface	
	the Primary Related Metering Point is no			Supplier Meter Registration	Relationships <u>MHHS IF-</u> 019 Maintain MPAN		
	longer required to be a Related Metering Point.			Agent	Relationships		Commented [SJ35]: Mop Up Update - added interface names throughout
4.3.2	Following 4.3.1 <u>and</u> within the timescales set out in the <u>BSCP706</u> .	Validate request to end a Related Metering Point relationship.	Electricity Retail Data AgentSupplier Meter Registration Agent		Internal Process		
4.3.3	Following 4.3.2 if request is not valid.	Provide notification that the request has failed validation and the reasons for failure.	Electricity Retail Data AgentSupplier Meter Registration Agent	Registered Supplier	D0386 Manage Metering Point MHHS IF- 020Relationships <u>TBC</u> Maintain MPAN Relationships Outcome	DTNDIP Interface	Commented [SJ36]: Post consultation update to reflect Programme confirmation that rejection is via the IF020 through DIN 105

14

Copyright 20232 Retail Energy Code Company

Commented [SJ34]: Mop Up Update - additional text to differentiate MHHS and Non MHHS requirements for transition

4.3.4	Following 4.3.2 if	Provide notification that the	Electricity Retail	Registered	D0386 Manage Metering	DTNDIP		
	request is valid.	request has been validated.	Data	Supplier	Point	Interface		
			AgentSupplier		RelationshipsMHHS IF-			
			Meter	DNO	020 Maintain MPAN			
			Registration	MEM MOA	Relationships Outcome		Cor	mmented [SJ37
			<u>Agent</u>					m MEM to MOA to
				Data Service				
				BSC Central				
				<u>Systems</u>				
				Electricity Enquiry				
				Service Provider				
4.3.5	Following 4.3.4, where	Update the end of a Related	Electricity Retail	CSS Provider	RMP Associations	CSS API		
	the ERDA becomes	Metering Point relationship.	Data Agent					
	aware of a valid							
	change to a Related							
	Metering Point							
126	relationship. Following 4.3.5 where	Perform asynchronous validation:	CSS Provider		Internal Process			
4.3.6	the message passes	Perform asynchronous valuation.	C33 PTOVIDEI		Internal Process			
	synchronous	If valid, update RMP Record.						
	validation.							
		If not valid, the CSS Provider shall						
		resolve the error in accordance						
		with the relevant Error Resolution						
		Paths.						

Commented [SJ37]: Mop Up Change - amended terminology from MEM to MOA to reflect approved CP R0064

15

4.3A The detailed process and timings for ending a Related Metering Point relationship where all Metering Points are Non-MHHS Metering Points are further described in the following interface table:

Ref	When	Action	From	То	Information Required	Method
<u>4.3.1A</u>	Where the Electricity Supplier identifies that	Update that the Related Metering Point relationship has ended.	<u>Registered</u> Supplier	<u>Electricity Retail</u> Data Agent	D0386 Manage Metering Point Relationships	
	<u>the Primary Related</u> Metering Point is no					
	longer required to be a Related Metering					
	Point.					
<u>4.3.2A</u>	Following 4.3.1A.	Validate request to end a Related Metering Point relationship.	Electricity Retail Data Agent		Internal Process	
<u>4.3.3A</u>	Following 4.3.2A if	Provide notification that the	Electricity Retail	Registered	D0386 Manage Metering	DTN
	<u>request is not valid.</u>	request has failed validation and the reasons for failure.	<u>Data Agent</u>	Supplier	Point Relationships	
<u>4.3.4A</u>	Following 4.3.2A if	Provide notification that the	Electricity Retail	Registered	D0386 Manage Metering	DTN
	<u>request is valid.</u>	request has been validated.	<u>Data Agent</u>	<u>Supplier</u>	Point Relationships	
<u>4.3.5A</u>	Following 4.3.4A.	Update the end of a Related Metering Point relationship.	<u>Electricity Retail</u> Data Agent	CSS Provider	RMP Associations	<u>CSS API</u>
<u>4.3.6A</u>	Following 4.3.5A where the message	Perform asynchronous validation:	CSS Provider		Internal Process	
	passes synchronous	If valid, update RMP Record.				
	<u>validation.</u>	If not valid, the CSS Provider shall				
		resolve the error in accordance				
		with the relevant Error Resolution				
1		Paths.				

16

Commented [SJ38]: Mop Up Update - additional table to differentiate MHHS and Non MHHS requirements for transition

5 Distribution Network Operator Management of Related Metering Points

- 5.1 All Related Metering Points must share the same RMP Status of Operational or Created and can not be changed to another status whilst they are within a relationship.
- 5.2 If a Primary Related Metering Point requires a RMP Status change to Terminated then the process set out within Paragraph 4 must be followed. The DNO can then set the RMP Status to Terminated as per the processes set out within the Switching Data Management Schedule.
- 5.3 If a Secondary Related Metering Point requires a RMP Status change to Terminated then the process set out within Paragraph 3 must be followed. The DNO can then set the RMP Status to Terminated as per the processes set out within the Switching Data Management Schedule.
- 5.4 For each Non Half Hourly-Whole Current Related Metering Point-maintained by the Electricity Retail Data Agent, the relevant DNO shall ensure that:

 - (b) the Primary Related Metering Point and the Secondary Related Metering Point(s) within a relationship___identified by the applicable Line Loss Factor Code, are subject to the same unit charges (per kWh) as part of the DNO's Distribution Use of System Charges.

6 Data Quality Requirements

- 6.1 Where an Electricity Supplier identifies that Metering Points meet the criteria in Paragraph 1.2 and a Related Metering Point relationship has not been established, the Electricity Supplier shall establish a Related Metering Point relationship in accordance with Paragraph 2.4.
- 6.2 Where an Electricity Supplier identifies that a Related Metering Point relationship has erroneously been established then the Electricity Supplier shall resolve the erroneous relationship to ensure compliance with this REC Schedule. Where this requires communication with other Electricity Suppliers or the DNO, the Electricity Supplier shall communicate via the SDEP using the RMP Data Quality Market Message.
- 6.3 If a DNO identifies that Metering Points meet the criteria in Paragraph 1.2 and a Related Metering Point relationship has not been established, the DNO shall inform the Registered Supplier, together with the rationale, via the SDEP using the MPAS Data Error Resolution Market Message.
- 6.4 For Half Hourly Metering Points, wWhere a DNO makes changes which result in the Metering Points meeting the criteria in Paragraph 1.2(b), the DNO shall inform the Registered Supplier, together with the rationale, via the SDEP using the MPAS Data Error Resolution Market Message.

Commented [SJ39]: Post consultation update - added Created following confirmation that new relationships can be established for Metering Points with a status of Created as part of DIN105