

Message Flow Details

MM00074 - Allocation of New/Additional MPAN Core(s)

Market Message Information

Market Message Reference	MM00074
MM Description	The Distributor sends the requested number of MPAN Cores to the Supplier.
Local Catalogue Reference	D0169
Version	001
Notes	Metering Point Postcode should only be omitted if the Post Office have not allocated one. Though all of the address data items included in this flow are defined within the structure as being optional, the address itself is mandatory and must be included in the flow. The address will be in Standard Address Format (SAF).

Scenario Variants

Scenario Variant	Name	Source	Target	Owner	Api Route	Api Method
SV00074	Allocation of New/Additional MPAN Core(s)	Electricity Supplier	Electricity Meter Equipment Manager	Retail Energy Code Company		
<u>SVxxxxx</u>	<u>Allocation of New/Additional MPAN Core(s)</u>	<u>Electricity Supplier</u>	<u>Electricity Smart Meter Equipment Manager</u>	<u>Retail Energy Code Company</u>		
<u>SVxxxxx</u>	<u>Allocation of New/Additional MPAN Core(s)</u>	<u>Electricity Supplier</u>	<u>Electricity Advanced Meter Equipment Manager</u>	<u>Retail Energy Code Company</u>		

Flow Structure

MM00074 - Allocation of New/Additional MPAN Core(s) - Message Structure

Group ID	Group Description	Range	Condition	L1	L2	L3	L4	L5	L6	L7	L8	Data Item Name	Data Item Rule
348	Metering Point Address Details	1-*	- Please reference Address Population Guidance v1.0.	G									
					0							Metering Point Address Line 1	
					0							Metering Point Address Line 2	
					0							Metering Point Address Line 3	
					0							Metering Point Address Line 4	
					0							Metering Point Address Line 5	
					0							Metering Point Address Line 6	
					0							Metering Point Address Line 7	
					0							Metering Point Address Line 8	
					0							Metering Point Address Line 9	
					0							Metering Point Postcode	
					0							Additional Information	
349	Additional/New MPAN Core(s)	1-*		G									
						1						MPAN Core	