

Message Flow Details

MM00099 - Issue Customer Key

Market Message Information

Market Message Reference	MM00099
MM Description	Details are being provided to allow the issue of a customer key.
Local Catalogue Reference	D0190
Version	001
Notes	<p>Though all of the address data items included in this flow are defined within the structure as being optional, the address itself is mandatory and must be included in the flow. The use of any individual address item cannot be made mandatory as, in the absence of an agreed address structure for all flows, an address may be constructed from any combination of the Address Line and Postcode items. Where flow is being sent for a CoS event, then EfSD{REGI} should be populated with the Supplier Start Date for that registration as confirmed by MPAS. Where flow is being sent for a CoM event, then EfSD{REGI} should be populated with date of meter installation (J0848) taken from relevant D0193 or D0150. Where flow is being sent for a CoT event, then EfSD{REGI} should be populated with the date that new tenant takes over that property as detailed within relevant Supplier system.</p>

Scenario Variants

Scenario Variant	Name	Source	Target	Owner	Api Route	Api Method
-------------------------	-------------	---------------	---------------	--------------	------------------	-------------------

SV00098	Issue Customer Key	Electricity Supplier	Electricity Meter Equipment Manager	Retail Energy Code Company		
SV00099	Issue Customer Key	Electricity Supplier	Electricity Pre-Payment Metering Infrastructure Provider	Retail Energy Code Company		
<u>SVxxxxx</u>	<u>Issue Customer Key</u>	<u>Electricity Supplier</u>	<u>Electricity Smart Meter Equipment Manager</u>	<u>Retail Energy Code Company</u>		

Flow Structure

SV00098 - Issue Customer Key - Message Structure

Group ID	Group Description	Range	Condition	L1	L2	L3	L4	L5	L6	L7	L8	Data Item Name	Data Item Rule
390	Customer Key Details	1-*	- Please reference Address Population Guidance v1.0.	G									
					0							Meter Id (Serial Number)	
					1							Key Infrastructure Supplier Id	
					1							Customer Reference Number	
					1							Tariff Setting	
					1							Emergency Credit	
					1							Total Debt	

				1						Debt Recovery Rate	
				1						Initial Key Credit	
				1						Reason Code	
				1						Effective from Settlement Date {REGI}	Effective from Settlement Date {REGI} must be the Supplier Start Date for a Switch event; or the date that a tenant first occupies a premises for a Change of Occupier event; or the date of meter installation for a Change of Measurement event.
				1						Customer Name	
				0						Metering Point Address Line 1	
				0						Metering Point Address Line 2	
				0						Metering Point Address Line 3	
				0						Metering Point Address Line 4	
				0						Metering Point Address Line 5	
				0						Metering Point Address Line 6	
				0						Metering Point Address Line 7	

				0						Metering Point Address Line 8	
				0						Metering Point Address Line 9	
				0						Metering Point Postcode	
				0						Mailing Name	
				0						Mailing Address Line 1	
				0						Mailing Address Line 2	
				0						Mailing Address Line 3	
				0						Mailing Address Line 4	
				0						Mailing Address Line 5	
				0						Mailing Address Line 6	
				0						Mailing Address Line 7	
				0						Mailing Address Line 8	
				0						Mailing Address Line 9	
				0						Mailing Address Postcode	
				1						MPAN Core	